

PS1000 / 14486



Features and Benefits

Fire up a pedalboard anywhere using our PS1000 Rechargeable Pedal Power Bank. While this power bank eliminates the inconvenience of running an extension cord or finding an outlet near the front of a stage, it also provides the freedom to use pedals with a battery-powered amp outdoors. Plus, this power bank avoids the buzz and hum caused by grounding issues in a venue or home. Several pedals or an entire small pedalboard can be powered using this power bank with the included daisy chains—no need for individual adapters. The battery-life indicator takes the guesswork out of determining how much power remains and the built-in flashlight makes it easier to navigate a candlelit venue or the woods around a campfire.

Specifications

Application: Effect pedal power

Recharging Voltage: 5 V (micro-USB charging cable included)

Battery life varies depending on total current draw being used. At maximum current draw: 6 hours (one 9 V output), 3 hours (two 9 V outputs), 1 hour (two 9 V outputs + 5 V output). Most applications will use less than maximum power consumption, therefore increasing battery life.

Full Recharging Time: 5 hours

Two 9 V outputs (center negative)

9 V Output Current: 1.2 A

One 5 V USB output

5 V Output Current: 2 A

One LED flashlight

Power Capacity: 10,000 mAh, 3.7 V Li-ion battery

9 V Output Ripple: 70–80 mV

Power Consumption in Standby Mode: 120 μ A

Dimensions: 5.8" x 2.6" x 0.7"

Weight: 0.5 lb

Includes: Power bank, micro-USB cable, (2) daisy chains

